# Intrinsically safe 4-20 mA loop powered sensors









Via Italo Calvino 7 Lotto 1 - Edificio A13-14 20017 Rho (MI) Tel. +39 02 36569371 info@danetech.it www.danetech.it



True RMS or peak output
Certified intrinsically safe for use in hazardous areas

 Easily integrated into existing process control

· Manufactured in an

approved ISO 9001 facility

systems

**Key features** 

#### Table 1: PC420Ax-yy-IS model selection guide

x (4-20 mA output type)	yy (full scale)	
R = acceleration, RMS P = acceleration, equivalent peak TP = acceleration, true peak	05 = 5 g (49 m/sec <sup>2</sup> ) 10 = 10 g (98 m/sec <sup>2</sup> ) 20 = 20 g (196 m/sec <sup>2</sup> )	

#### Certifications



Class I, Div 1 Groups A, B, C, D T3C

 $Ta = 85^{\circ}C \text{ max}$ 



II 1 G Ex ia IIC T4 Ga -40°C ≤ Ta ≤ +85°C





For hazardous area locations, sensor must be installed in accordance with installation diagram 12779. Refer to installation diagram 12779 for correct method of grounding the safety barrier. The apparatus must be connected to certified intrinsically safe equipment with electrical parameters as specified below:

T4 V < U $_{\circ}$  < 30V, 20 mA < I $_{\circ}$  < 106 mA (linear supply only), P $_{\circ}$  < 0.75 W Furthermore, the following conditions must be satisfied:

 $C_{o} < C_{i} + C_{cable}$  and  $L_{o} < L_{i} + L_{cable}$ Maximum cable length: 100 ft (31 m)  $C_{cable}$ : 6 nF for 100 ft.



Note: Due to continuous process improvement, specifications are subject to change without notice. This document is cleared for public release.

Wilcoxon Sensing Technologies An Amphenol Company

8435 Progress Drive Frederick, MD 21701 USA Tel: +1 (301) 330-8811 Fax: +1 (301) 330-8873 info@wilcoxon.com

buy.wilcoxon.com www.wilcoxon.com

# Intrinsically safe 4-20 mA

## loop powered sensors



### PC420A-IS series

#### **SPECIFICATIONS**


Output, 4-20 mA:		
Full scale, 20 mA, ±5%		see Table 1 on page 1
Frequency response:	±10% ±3 dB	10 Hz - 1.0 kHz 4.0 Hz - 2.0 kHz
Repeatability		±2%
Transverse sensitivity, ma	X	5%
Power requirements, 2-wire lo Voltage at sensor terminal	• •	12 - 30 VDC
Loop resistance <sup>1</sup> at 24 VDC, m	ıax	600 Ω
Turn on time, 4-20 mA loop		<30 sec
Grounding		case isolated, internally shielded
Operating temperature range		–40° to +85° C
Vibration limit		250 g peak
Shock limit		2,500 g peak
Sealing		hermetic
Sensing element design		PZT, shear
Weight		162 grams
Case material		316L stainless steel
Mounting		1/4-28 tapped hole
Output connector		2 pin, MIL-C-5015 style
Mating connector		R6 type
Recommended cabling		J9T2A


Accessories supplied: SF6 mounting stud (metric mounting available); calibration data (level 2)

Notes: 1 Maximum loop resistance (R<sub>1</sub>) can be calculated by:

$$R_{L} = \frac{V_{DC power} - 10 \text{ V}}{20 \text{ mA}}$$

DC supply voltage	R <sub>L</sub> (max resistance) <sup>2</sup>	R <sub>L</sub> (minimum wattage capability) <sup>3</sup>
20 VDC	400 Ω	1/4 watt
24 VDC	600 Ω	1/2 watt
26 VDC	700 Ω	1/2 watt





Note: Due to continuous process improvement, specifications are subject to change without notice. This document is cleared for public release.

 $<sup>^{2}</sup>$  Lower resistance is allowed, greater than 10  $\Omega$  recommended.

<sup>&</sup>lt;sup>3</sup> Minimum R<sub>1</sub> wattage determined by: (0.0004 x R<sub>1</sub>).